

Clearing Maintenance from an Aurelia Wave Digit/T3

- Enter the menu by pressing the three horizontal lines in the top right corner of the display screen
- Swipe the screen left or press the arrow in the bottom right corner of the screen
- Select the **Settings** button
- Select the **Alarms** button (If there is not an **Alarms** button, go to **Diagnostics**, then **General Diagnostics**)
- Select the **Maintenance Alarm** button
- hold the “Zero the inner counter” button until it reads “counter zeroed”
- Advance the date
- Exit the menu by pressing the three horizontal lines in the top right corner of the screen